


Technical specifications. Mixers/Unmixers SAT/TER. AM series


		AM	AM 2
Code		0980000	0980001
Inputs		2 (TER / SAT)	3 (TER / SAT1 / SAT2)
Outputs		1 (TER + SAT)	2 (TER+SAT1 / TER+SAT2)
Frequency margin (MHz)	TER	5 - 862	5 - 862
	SAT	950 - 2400	950 - 2400
Insertion loss (dB)	TER	1,5	4,5
	SAT	2	2
Decoupling between bands (dB)		>25	>25
Impedance (Ohm)		75	75
Installation type		Indoor	Indoor
Current pass		SAT	SAT
Connectors		F female	F female
Plastic support		Included	Not included
Dimensions without support (mm)	(W x H x D)	51,9 x 50 x 16,5	74 x 58,1 x 17,8
Dimensions with support (mm)	(W x H x D)	57 x 50 x 26,5	79,2 x 58,1 x 27,3
Packing quantity		1 / 10 / 120	1 / 12 / 144

Passive elements assembly with plastic base

1. Assembly of plastic base inside the register or wall. Fix with screws.



2. Cables connection to passive element.



3. Press to fix the passive element to the base.

