

FILTROS LTE **FE 690 / FE 686**
 FILTRES LTE **FE 690 / FE 686**
 FILTRI LTE **FE 690 / FE 686**
 FILTROS LTE **FE 690 / FE 686**
 LTE FILTERS **FE 690 / FE 686**



REFERENCIA	RÉFÉRENCE	ARTICOLO	REFERÊNCIA	REFERENCE		FE 690	FE 686
Banda de paso	Bande passante	Banda passante	Banda de passagem	Passband	MHz	5 - 694	5 - 686
Pérdidas de paso	Affaiblissement de passage	Perdite di passaggio	Perdas inserção	Insertion loss	dB 5-678 MHz	<0,8	<1
					dB 686 MHz	<1	<3,5
					dB 690 MHz	<3,5	<12
					dB 694 MHz	<12	>25
					dB 698 MHz	>25	>25
Banda rechazada	Bande réjectée	Attenuazione banda LTE	Banda de rejeição	Stop band	MHz	694-862	698-862
Conectores	Connecteurs	Connettori	Conectores	Connectors		2x F Hembra	
Paso de corriente	Passage de courant	Passaggio DC	Passagem de corrente	DC Pass	mA	300	
Uso típico	Utilisation typique	Uso tipico	Uso típico	Typical application		Exterior Outdoor	
Dimensiones	Dimensions	Dimensioni	Dimensões	Dimensions	mm	109 x 96 x 56	