

INDOOR MICRO AMPLIFIERS

MAA 20 L1 · MAA 20 L2 · MAA 22

- ✓ Ultra compact design
- ✓ Two options: direct mounting to TV socket through the IEC connector (models MAA 20 L1 and L2) or wall-mount (MAA 22)
- ✓ Linear attenuation in 5dB steps
- ✓ 2 asymmetric outputs (MAA 20 L1 and L2 models)



MAA 20 L1 / L2



MAA 22

TECHNICAL TABLE

REFERENCE		MAA 20 L1	MAA 20 L2	MAA 22
Code		111008	111010	111009
Inputs	N.	1	1	1
Outputs	N.	2	2	1
Frequency Range	MHz	47-790	47-694	5-65 / 88-1000
Gain	dB	OUT 1: 18 OUT 2: 22	OUT 1: 18 OUT 2: 22	22
Regulation	dB	5-10	5-10	5-10
Return path loss	dB	-	-	1
Output level DIN 45004B	dBμV	OUT 1: 102 OUT 2: 106	OUT 1: 102 OUT 2: 106	110
Return loss	dB	>10		
Noise figure	dB	<4		
Mains voltage	Vac	12Vdc*		
Current consumption	W	2,2		
Dimensions	mm	65 x 47 x 21		

*Included