

# MAST AMPLIFIERS

AM 311 L2 · AM 381 L2

Ltè2

- ✓ Excellent gain / output level ratio
- ✓ Low noise factor
- ✓ ABS plastic case, IP 23, with self-supporting lid and closure for coaxial cables
- ✓ Swivel amplifier for easy connection.
- ✓ DC current pass at UHF input

**Ek** EKSELANS BY ITS



AM 311 L2



AM 381 L2

## TECHNICAL INFORMATION

REFERENCE		AM 311L2	AM 381L2
Code		051024	051026
Inputs		UHF	UHF
Frequency range	MHz	470-694	470-694
Gain	dB	35	40
Regulation	dB	15	15
Output level (DIN 45004B)	dBμV	110	114
Noise factor	dB	<2	<2
Mains voltage	Vdc	24	24
DC Pass		✓	✓
Current consumption	mA	≤ 70	≤ 85
Second output / test	dB	-	-20