

# POWER SUPPLIES



FA QC 24 · FA QC 242 ·  
FA QC 12 · FA QC 122

- ✓ Switched power supplies
- ✓ Ultra-compact size
- ✓ Suitable for 80x80mm junction box
- ✓ Easy to install, just a few seconds
- ✓ QuiCoax connection system
- ✓ Zamak quicoax case high protection
- ✓ Working led indicator
- ✓ **New generation quicoax system, even easier connection**



FA QC 242



80x 80 mm junction box  
installation

01



Reduce to  
minimum  
**installation time**

02



**No need  
of tools**

03



Guarantees  
an **excellent  
connected** and  
minimizes the  
**space**

04



Very high  
**shielding factor  
CLASS A +10dB**  
throughout the  
band

05



Eliminate the use  
of **connectors**  
and **associated  
costs**

06



**QuiCoax,  
the new  
Standard of  
Connection**



## TECHNICAL TABLE

REFERENCE		FA QC 24	FA QC 242	FA QC 12	FA QC 122
Code		053003	053004	053001	053002
Outputs	N°	1	2	1	2
Frequency range	MHz	47-1000	47-1000	47 - 2150	47 - 2150
Insetrion loss	dB	<2	<4	<2	<4
Output voltage	Vdc	24	24	12 / 13-18	12 / 13-18
Maximum current output	mA	150	150	250	300
Power supply	Vac	100/240	100/240	100/240	100/240
Dimensions	mm	62 x 60 x 22			